EXP5040A USER MANUAL
Trio 3D

- **Installing on Windows 95**

Due to the plug & play feature of Windows 95, if it is the first time you install a new VGA card and star Windows 95
, Windows will prompt you that a new device is installed nad ask you to insert the driver diskette. In this case, please insert the setup CD into CD-ROM. (Assume your CD-ROM driver is on driver D:, if it is not, change D: to other driver letter.) then input the driver sourceas.
D:\TRIO3D(as a EXP5040A)
after that, Windows will prompt you again to select the driver type, please select " S3 Inc Trio3D".
Windows will copy driver files and ask you to restart Windows, you need to restart Windows so that the new driver will take effect.

Verifying Driver Installation

1. From the Windows 95 desktop, click on "My Computer", then "Control Panel", and then, finally, "System".
2. You should be in the "System Properties" window. Click on the "Device Manager" tab. From here, go down to "Display Adapter" and click. The drivers associated with the display adapter should read: "S3 Inc. Trio3D". If this is not the case, the drivers will need to be re-installed.

Installing on Windows NT4.0

General Installation Notes

Before install Windows NT 4.0 Driver, Please install Microsoft Service pack 3 First.

1. After Windows NT 4.0 has loaded, click on "My Computer" icon, "Control Panel" icon, and then the "Display" icon.
2. You should now be in the "Display Properties" window. Select the "Settings" tab, and click on the "Display Type" button.
3. "Display Type" window, click the "Change..." button.
4. From the new window, click on the "Have Disk" button.
5. You should now be in the "Install From Disk" window. In the "Copy manufactures files from:" box, place the CD-ROM in the proper drive and click the "Browse..." button. The drivers are located in the "\C365_S3\NT40" directory of the CD-ROM. When the correct directory is chosen, click "OK" to continue the installation.
6. A window should pop up stating that the "S3 Incorporated Trio3D Display" drivers are about to be installed. Click the "OK" button to accept the display driver change, and then click the "Yes" button in the "Third Party Drivers" window as well as the "OK" button in the "Installing Driver" window. Click "Close" on the "Display Properties" window to complete the installation. Restart the computer when prompted to do so.
7. After rebooting, the "Invalid Display Settings" window will appear. Press "OK" and change the resolution settings, if desired. If you choose to change the resolution and/or color depth settings, follow the instructions on the screen.

Verifying Driver Installation

From the Windows NT desktop, click on "My Computer" then "Control Panel" then "Devices". In the "Devices" window, under the "Device" column the driver associated with the display adapter should read:
"S3Inc" and the "Status" column next to the driver should read "Started". If this is not the case, the drivers will need to be re- installed.

Trio 3D

AGP Card